

AJAX-LC-2W-1-GANG

Ajax - LightCore (2 way) Relay for light Switch

Product Overview

Ajax - LightCore (2 way) Relay for light Switch, From 5 to 600 W Power of switched device, LightSwitch only needs a live wire to operate



Specifications

Specifications:

© 2024 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.	
Specifications	
Product Code	AJAX-LC-2W-1-GANG
Compatibility	
Hubs	Hub Plus
	Hub 2 (2G)
	Hub 2 (4G)
	Hub 2 Plus
	Hub Hybrid (2G)
	Hub Hybrid (4G)
Radio signal range extenders	ReX
	ReX 2
Communication	

ComX Computers

Product Specification Sheet

Jeweller communication technology	Proprietary wireless technology to transmit the commands and events.
	Features:
	Two-way communication.
	Protection against device spoofing.
	Block encryption featuring a dynamic key.
	Instant notifications.
	Remote configuration via the Ajax apps.
Radio frequency bands	866.0 - 866.5 MHz
	868.0 - 868.6 MHz
	868.7 - 869.2 MHz
	905.0 - 926.5 MHz
	915.85 - 926.5 MHz
	921.0 - 922.0 MHz
	Depends on the sales region.
Maximum effective radiated power (ERP)	up to 20 mW
	Automatic power control to reduce power consumption and radio interference.
Radio signal modulation	GFSK
Radio communication range	up to 1,100 m
	Between the device and a hub (or radio signal range extender) in an open space.
	Calculate radio communication range at the facility
Encrypted radio communication	All the data stored and transmitted are protected by block encryption with a dynamic key.
Frequency hopping	To prevent radio interference and jamming.
Features	
Scenarios	reaction to alarm
	reaction to security mode change
	activation by schedule
	reaction to pressing another LightSwitch
Operation without neutral wire	LightSwitch only needs a live wire to operate.
Power of switched device	from 5 to 600 W
Contactless touch panel	LightSwitch is activated when a hand gets as close as 15 mm from the panel.
Night backlight	Optional, can be turned off in the Ajax app device settings.
Protection against incompatible devices	Triggers if lighting devices have insufficient power (up to 5 W). If protection is triggered, LightSwitch turns off power and sends a notification to Ajax apps. For low-power lighting devices, the kit includes a capacitor.
	Recommendations
	The device is designed for indoor installation only. A professional electrician should install a device.
Anti-sabotage protection	

ComX Computers

Product Specification Sheet

Protection against spoofing	device authentication
Communication loss detection	from 36 seconds
	The time to detect the communication loss depends on the Jeweller (or Jeweller/Fibra) settings.
Power supply	
Power supply voltage	230 V, 50 Hz
	The device does not need a neutral wire to operate.
Average consumption	up to 200 mW
Maximum power	600 W
	For LightCore (1-gang) and LightCore (2-way).
	300 W per segment
	For LightCore (2-gang).
Current protection	more than 2.6 A
	If protection is triggered, LightSwitch turns off power and sends a notification to Ajax apps.
Temperature protection	more than +60 degreesC
	If protection is triggered, LightSwitch turns off power and sends a notification to Ajax apps.
Operating parameters	
Operating temperature range	from -10 degreesC to +40 degreesC
Operating humidity	Up to 75% with no condensation
Protection class	IP20
Form factor of the switch	European type (55)
Weight	
Relay	LightCore (1-gang) - 45.95 g
	LightCore (2-gang) - 53.9 g
	LightCore (2-way) - 48.34 g
Frames	Frame (2 seats) - 16.13 g
	Frame (3 seats) - 22.12 g
	Frame (4 seats) - 28.12 g
Buttons	SoloButton (1-gang / 2-way) - 44.5 g
	SoloButton (2-gang) - 45.75 g
	CenterButton (1-gang / 2-way) - 30.97 g
	CenterButton (2-gang) - 31.97 g
	SideButton (1-gang / 2-way) - 31.56 g
	SideButton (2-gang) - 32.73 g
Dimensions	

ComX Computers

Product Specification Sheet

Relay	LightCore (1-gang) - 76.3 x 72.3 x 29.2 mm
	LightCore (2-gang) - 76.3 x 72.3 x 29.2 mm
	LightCore (2-way) - 76.3 x 72.3 x 29.2 mm
Frames	Frame (2 seats) - 82.75 x 153.48 x 6.3 mm
	Frame (3 seats) - 82.75 x 224.48 x 6.3 mm
	Frame (4 seats) - 82.75 x 295.48 x 6.3 mm
Buttons	SoloButton (1-gang / 2-way) - 82.75 x 82.75 x 10.26 mm
	SoloButton (2-gang) - 82.75 x 82.75 x 10.26 mm
	CenterButton (1-gang / 2-way) - 82 x 70.53 x 10.26 mm
	CenterButton (2-gang) - 82 x 70.53 x 10.26 mm
	SideButton (1-gang / 2-way) - 82 x 76.19 x 10.26 mm
	SideButton (2-gang) - 82 x 76.19 x 10.26 mm

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page: <https://www.comx.co.za/AJAX-LC-2W-1-GANG-Ajax-LightCore-2-way-Relay-for-Buy-p-294668.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx.co.za/terms-of-sale.php>

PDF generated: 2026-10-07 22:35:35.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.