

# USB-CHARGER-P1112ABK

Unitek P1112ABK 100W 4 Ports GaN Power Delivery charger

## Product Overview

Unitek P1112ABK 100W 4 Ports GaN Power Delivery charger, USB-C x 2 Maximum 100W (USB Power Delivery supported), 2x USB-C Maximum 100W (USB Power Delivery supported), 1x USB-C Maximum 20W (USB Power Delivery supported), USB Type-A Maximum 18W (Quick Charge supported)



## Specifications

### Overview:

**Model Number:** P1112ABK

Gallium nitride (GaN) is a high-performance charger compare to the traditional silicon used in charging devices. It achieves high power output with a compact size, ideal for charging anywhere. This 4 ports Black GaN charger equips with 3 x USB-C PD ports and 1 x USB-A QC port, together with replaceable plugs working worldwide for your laptops like MacBook Air, or tablets and smartphones, even when you're travelling abroad.

### Features:

- Superior in craftsmanship and performance.
- Powerful GaN(gallium nitride) technology offers super-efficiency at current-transferring with low heat generation which also results in a compact and lightweight design.
- This travel charger can be applied globally. It equips foldable US plug and comes with EU, UK and AU adapter for replacement and supports the voltage-input under AC 100~240V, 50~60Hz, 1.7A Max.
- 3 USB-C ports, 1st and 2nd USB-C support up to PD 100W, and the 3rd one up to 20W.
- USB-A port support QC3.0 up to 18W and backward compatible.
- All 4 ports are able to work simultaneously and the power output will automatically process dynamic allocation from 65W to 7.5W. Please be reminded to plug in the high consumption devices first then others.
- Built-in four intelligent protection circuits against overvoltage, overcurrent, overheat and short circuit.
- With LED indicator, clearly express the working status.

### Specifications:

© 2022 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

### Specifications

|                          |                                                                          |
|--------------------------|--------------------------------------------------------------------------|
| <b>Product Code</b>      | USB-CHARGER-P1112ABK                                                     |
| <b>Colour</b>            | Black                                                                    |
| <b>Dimension</b>         | 63 x 63 x 30.5 (mm)                                                      |
| <b>Materials</b>         | Polycarbonate Plastic(PC)                                                |
| <b>Chipset</b>           | NN3379                                                                   |
| <b>Power Input</b>       | AC 100-240V, 50/60Hz. 2.5A                                               |
| <b>Power Output</b>      | -USB-C x 2: Max. 100W (USB Power Delivery Supported)                     |
|                          | -USB-C x 1: Max. 20W(USB Power Delivery Supported)                       |
|                          | -USB-A: Max. 18W(Quick Charge Supported)                                 |
|                          | Output:                                                                  |
|                          | Single Connection with USB-C1/USB-C2: Max 100W                           |
|                          | Single Connection with USB-C3: Max 20W                                   |
|                          | Single Connection with USB-A: Max 18W                                    |
|                          | Dual Connection with USB-C1 & USB-C2: 65W and 30W                        |
|                          | Dual Connection with USB-C1/C2 & USB-C3: 65W and 20W                     |
|                          | Dual Connection with USB-C1/C2 & USB-A: 65W and 18W                      |
|                          | Dual Connection with USB-C3 & USB-A: 7.5W and 7.5W                       |
|                          | Triple Connection with USB-C1, USB-C2, USB-C3: 45W, 30W and 20W          |
|                          | Triple Connection with USB-C1, USB-C2, USB-A: 45W, 30W and 18W           |
|                          | Triple Connection with USB-C1/C2, USB-C3, USB-A: 65W, 7.5W and 7.5W      |
|                          | Quadruple Connection: USB-C1 45W, USB-C2 30W, USB-C3 7.5W and USB-A 7.5W |
| <b>Packaging Content</b> | 1 x 100W 4 Potrs GaN Wall Charger                                        |
|                          | 1 x User Manual                                                          |
|                          | 1 x EU Plug                                                              |
|                          | 1 x UK Plug                                                              |
|                          | 1 x AU Plug                                                              |

## Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

**Product page:** <https://www.comx.co.za/USB-CHARGER-P1112ABK-Unitek-P1112ABK-100W-4-Ports-GaN-Buy-p-266152.php>

---

*Images and specifications are provided for reference and are subject to change without notice. E&OE.*

Terms of Use: <https://www.comx.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx.co.za/terms-of-sale.php>

---

PDF generated: 2026-10-20 10:24:06.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.