

DS-PM1-I1-WE

Hikvision DS-PM1-I1-WE Single Input Transmitter

Product Overview

Hikvision DS-PM1-I1-WE Single Input Transmitter For Wireless Ready Detector 868mhz 2way Communication Up To 1700m



Specifications

Features:

- Small size design, which can be put into wired detector easily
- 868MHz two-way wireless communication
- LED display, show the real status of device
- With one tamper input and one PGM, can be used as zone input or alarm output
- With 3.3V voltage output, can be used to power up external wired detector
- Detection of device removal by accelerometer

Specifications:

© 2023 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	DS-PM1-I1-WE
Hardware features	
Serial port	1
Power switch	1
Alarm input	1 Alarm, 1 Tamper
Alarm output	1 PGM, AM/Output
3.3v Output	1, up to 10mA
Electrical characteristics	
Power supply	3 CR123

ComX Computers

Product Specification Sheet

Operation humidity	10% to 90%
Operation temperature	-10 degreesC to 55 degreesC
Power consumption	Quiescent current: 40.29 uA
	Max current: 47.85 mA
	Voltage: 3 VDC
Battery life span	Up to 5 years (standby time)
Wireless transmission	
RF frequency	868 MHz
RF method	Two-way communication
RF modulation	2GFSK
RF distance	1700 m
Display	
Indicator	3: Alarm/Tamper(Red), Fault(Amber), Signal Strength(Green/Red)
General	
Installation method	Put inside wireless ready detector
Dimension(WxHxD)	102 mm x 41 mm x 20 mm
Weight	35 g (without battery), 90 g (with battery)

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page: <https://www.comx.co.za/DS-PM1-I1-WE-Hikvision-DS-PM1-I1-WE-Single-Input-Transmitter-Buy-p-284886.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx.co.za/terms-of-sale.php>

PDF generated: 2026-10-08 16:19:26.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.