

NET-ARCHER-T6E

TP-Link T6E AC1300 Wireless Dual Band PCI Express Adapter

Product Overview

TP-Link T6E AC1300 Wireless Dual Band PCI Express Adapter, 867 Mbps at 5GHz, 400 Mbps at 2.4GHz, 2x Dual Band detachable antennas



Specifications

Overview:

Archer T6E - AC1300 Wireless Dual Band PCI Express Adapter

- Easy Installation - Upgrade your desktop system easily by plugging the Archer T6E Wi-Fi adapter into an available PCI-E slot
- Hi-Speed Wi-Fi - Up to 1300Mbps Wi-Fi speeds (867Mbps on 5GHz band or 400Mbps on 2.4GHz band)
- 802.11ac Dual Band - 3 times faster than the 802.11n standard, perfect for hi-intensity network usage
- Backward Compatibility - With support for 802.11 a/b/g/n standards
- Broad Wireless Range - 2 external antennas ensure a greater range of Wi-Fi connection and stability

Features:

802.11ac - The Next Generation of Wi-Fi

TP-LINK's Archer T6E supports the next generation Wi-Fi standard - IEEE 802.11ac, offering transfer rates that are 3 times faster than wireless N speeds. Easily upgrade your desktop system by simply slotting the Wi-Fi adapter into an available PCI-E slot.

AC1300 - Selectable Dual Band Speeds 867/400Mbps

The Archer T6E provides high-speed Wi-Fi of up to 867Mbps over 5GHz, perfect for HD video streaming and lag-free online gaming. Additionally, the 2.4GHz 400Mbps Wi-Fi band is ideal for standard network/internet usage such as web surfing.

Heat Sink for Better Stability

The Heat Sink helps to dissipate heat generated by the adapter, which in turn increases performance and improves stability. What's more, lower temperatures ensure an increased adapter lifespan.

Specifications:

© 2024 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.	
Specifications	
Product Code	NET-ARCHER-T6E
HARDWARE FEATURES	
Interface	PCI Express
Dimensions (W x D x H)	4.8 x 4.5 x 0.85 in. (120.8 x 115.2 x 21.5 mm)
Antenna Type	2 Dual Band Detachable Antennas
WIRELESS FEATURES	
Wireless Standards	IEEE 802.11ac/n/a 5GHz
	IEEE 802.11b/g/n 2.4GHz
Frequency	2.4GHz or 5GHz
Signal Rate	867Mbps at 5GHz
	400Mbps at 2.4GHz
Reception Sensitivity	5GHz :-
	11a: -68dBm
	11n HT20: -64dBm
	11n HT40: -61dBm
	11ac HT20: -59dBm
	11ac HT40: -54dBm
	11ac HT80: -51dBm
	2.4GHz :
	11b: -76dBm
	11g: -68dBm
	11n HT20: -64dBm
	11n HT40: -61dBm
Transmit Power	5GHz :-
	2.4GHz :-
Wireless Modes	Ad-Hoc / Infrastructure mode
Wireless Security	Support 64/128 bit WEP, WPA-PSK/WPA2-PSK, 802.1x

ComX Computers

Product Specification Sheet

Modulation Technology	DBPSK, DQPSK, CCK, OFDM, 16-QAM, 64-QAM, 256-QAM
OTHERS	
System Requirements	Windows 10/8.1/8/7/XP (32/64bits)

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page: <https://www.comx.co.za/NET-ARCHER-T6E-TP-Link-T6E-AC1300-Wireless-Dual-Band-Buy-p-294897.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx.co.za/terms-of-sale.php>

PDF generated: 2026-10-10 12:26:32.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.