NET-MER-MU6H

Mercusys MU6H AC650 High Gain Wireless Dual Band USB Adapter

Product Overview

Mercusys MU6H AC650 High Gain Wireless Dual Band USB Adapter



Specifications

Overview:

MU6H receives Wi-Fi signals on two separate bands. Supporting 256-QAM technology increases 2.4 GHz data rate from 150 Mbps to 200 Mbps for 33% faster performance. Choose the 2.4 GHz for surfing and social media, and 5 GHz for up to 433 Mbps for HD streaming and lag-free gaming.

Features:

Boost Wireless Range with High Gain Antenna
A 5 dBi high gain antenna reaches your router from farther with more precise directional range, sustaining faster and more stable wireless connections.

Smart Easy-Install for Windows
An internal driver means you just need to plug MU6H into the computer and follow the on-screen directions to set up your network in seconds.

Adjustable, Multi-Directional Antenna
Rotate and adjust the antenna in multi-direction to improve using experience and performance in different environments.

Operating System
Fully compatible with Windows 10/8.1/8/7/XP

Advanced Security
WPA/WPA2 encryption standards keep your wireless connection safe from intruders.

Specifications:

© 2020 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications

Product Code	NET-MER-MU6H
Antenna Type	1 External High Gain
	5dBi Antenna
Dimensions (W X D X H)	2.28 x 0.66 x 6.83 in
	(57.8 x 16.8 x 173.4 m)
Wireless Standards	IEEE 802.11b/g/n
	IEEE 802.11a/n/ac
Wireless Security	WEP, WPA/WPA2
	WPA-PSK/ WPA2-PS
	802.1X
System Requirements	Windows10/8.1/8/7/XP
Interfaces	USB 2.0
Frequency	2400 MHz -2483.5 MHz
	5150 MHz -5250 MHz
	5250 MHz -5350 MHz
	5470 MHz -5725 MHz
LED	Status
Signal Rate	11ac: Up to 433Mbps (Dynamic)
	11n: Up to 200Mbps (Dynamic)
Reception Sensitivity	433M: -62dBm@10% PER
	200M: -65dBm@10% PER
	54M: -75 dBm@10% PER
	11M: -90 dBm@8% PER
Package Contents	1. AC650 High Gain Wireless Dual Band USB Adapter (MU6H)
	2. Quick Installation Guide

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx.co.za/NET-MER-MU6H-Mercusys-MU6H-AC650-High-Gain-Wireless-Dual-Band-USB-Adapter-p-246069.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx.co.za/terms-of-use.php
Terms of Sale: https://www.comx.co.za/terms-of-sale.php

PDF generated: 2026-11-19 16:52:14.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.