



Your Efficient All-in-One Mono Laser Printer

Easy to set up and connect for
Fast Flawless printing

MFC-L2805DW



PRINT



SCAN



COPY



FAX

www.brother.co.za

Your Efficient All-in-One Mono Laser Printer

Work from anywhere, at home or in the office with the easily connected Brother MFC-L2805DW. Hosting a range of efficiency-boosting features, this all-in-one mono laser printer saves you time with fast flawless printing and quick scan speeds, automatic 2-sided print, fax capability, a generous paper tray capacity and large automatic document feeder.

Set up with ease and download the Brother Mobile Connect App, enabling you to print and scan from virtually anywhere.

MFC-L2805DW



Key features:

- Print up to 34 pages per minute
- Auto duplex print, up to 16 sides per minute
- 2 Line LCD control panel
- Fast ethernet, 2.4GHz Wi-Fi Direct and USB
- 256MB Memory
- 50 Sheet Automatic Document Feeder (ADF) ¹¹
- 250 Sheet paper input tray ¹¹
- 1,200 Page yield inbox toner
- 3,000 maximum yield available ⁷

Work smarter

The MFC-L2805DW is designed to increase efficiency, with fast print speeds helping you to work smarter. The Automatic Document Feeder and 2-sided print feature saves you time, enabling you to get on with other tasks. Scan your documents in colour or mono and send directly to your desktop or mobile device.

Effortless

Make your day easier and your printing effortless, with simple set up and fast wireless, ethernet or USB connection. This efficient MFC-L2805DW is a breeze to operate using the easy to navigate control panel.

The perfect partner

High quality print technology ensures that your output is flawless and professional every time. The expertly designed MFC-L2805DW has a high capacity paper input and output tray allowing you to print for longer, while the compact and quiet form enables you to work without interruption in smaller workspaces.

Print longer

The MFC-L2805DW keeps your printing costs down using a separate drum and toner unit, and the 1,200 pages⁷ inbox toner supporting your higher print volume needs. Toner is easy to change and a high yield toner is available, printing up to 3,000 pages⁷⁷, reducing your cost per page and replacement frequency.

Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The MFC-L2805DW provides a range of robust features. It uses triple-layer security at a device, network and document level. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.

Print from anywhere

With Brother Mobile Connect, you can fully operate your Brother printer from anywhere. Print and scan documents on the move. You can also personalise your frequently used features and unlock a revolutionary way of printing from your mobile device. Download the app on your mobile device to get started.



General	Technology Electrophotographic Laser	Local Interface Hi-Speed USB 2.0	Carton Contents Printer, Inbox Toner, Drum, Power Supply Cord, USB Cable, Quick Set-Up Guide
	Memory 256MB	Wired Network Fast Ethernet	
	Control panel 2 Line LCD with keys White Back Light	Wireless Network 2.4GHz Support Wi-Fi Direct	
Print	Print Speed 1-Sided: 34ppm Mono 2-Sided: 16 sides per minute Mono	Quiet Mode A mode to reduce the printing noise	Embedded Barcodes (PCL) 16 bar codes* *Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI
	FPOT (First Print Out Time) Up to 8.5 Seconds Mono	Print Languages PCL6, BR-Script3, PDF Version 1.7	
	Resolution Up to 1200 x 1200dpi	Embedded Fonts (PCL) 73 scalable fonts, 12 bitmap fonts	Embedded Fonts (Postscript) 66 scalable fonts
Printer Functions	N-up Printing Reduce pages into a single page layout	ID Printing Add identification to your printed documents (date and time, short custom message or PC username)	Manual 2-Sided Print Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)
	Poster Printing Enlarge a single page into a poster using 2x2, 3x3, 4x4 or 5x5 pages	Booklet Printing Print documents in A5 booklet format using automatic or manual 2-sided print	Reverse Print Rotate the content of a printed document by 180°
	Toner Save Mode Use the Toner Save Mode to reduce toner consumption without affecting print speed	Print Profiles Store your favourite driver settings as profiles to easily recall them	Print Complete Notice A printing notification can be set to go to your computer (Network only)
	Watermark Printing Watermark your documents with predefined text, custom logo or custom messages		
Printer Driver	Windows Windows 11 (32 and 64 bit editions) and more	macOS Printing via macOS requires the use of AirPrint. Mac drivers are not provided.	Linux CUPS, LPD/LPRng (x86/x64 environment)
	ChromeOS (Print/Scan Only) Supports native ChromeOS printing		PCL Driver Universal Printer Driver (Windows) (PCL5e/BRScript)
	Visit support.brother.com for the full list of supported OS and		

MFC-L2805DW | Page 4

Paper Handling ¹¹

Paper Input
Standard Tray
250 Sheets

Manual Feed Slot
1 Sheet

Automatic Document Feeder (ADF)
50 Sheets

Paper Output
120 Sheets A4

Envelope Printing
From manual feed slot

Media Sizes
Standard Tray
A4, Letter, B5(JIS), B5(ISO), A5, A5(Long Edge), B6(JIS), A6, Executive, A4 Short, 16K(195x270mm)

Manual Feed Slot
Width 76.2 to 215.9 mm, Length 127 to 355.6 mm Envelope; COM-10, DL, C5, Monarch

ADF
Width: 105 to 216 mm Length: 147 to 356 mm

Scanner Glass
Up to A4/LTR

Auto 2-Sided
A4

Media Type and Weights
Standard Tray
Plain Paper, Thin Paper, Recycled Paper, Thick Paper 60-163gsm

Manual Feed Slot
Plain Paper, Thin Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond, Label, Envelope, Env. Thin, Env. Thick 60-230gsm

ADF
Plain Paper, Recycled Paper 60 to 105gsm

Auto 2-Sided
Plain Paper, Thin Paper, Recycled Paper 60-105gsm

Mobile and Web Connectivity

Brother Mobile Connect ¹⁷ (Android)
Print from, scan to, preview copies and check the machine status from an Android device

Brother Mobile Connect ¹⁷ (iPad / iPhone)
Print from and check the machine status from an iPad / iPhone

Apple AirPrint ¹⁷
Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin ¹⁷
Print from any Android devices without a dedicated App.

Mopria™ ¹⁷
Print most common file types from Mopria™ supported Android devices

Copy

Copy Speed
34ppm Mono (Manual / Duplex)

Resolution
Up to 600 x 600dpi

FCOT
(First Copy Out Time)
Up to 10 Seconds Mono

Grey Scale
256 shades of grey

Copy Functions

Multi-Copying/Stack/Sort
Makes up to 99 copies of each page / Stacks or Sorts

Enlargement/Reduction Ratio
Reduce or Increase document sizes from 25% to 400% in 1% increments

N in 1 Copying
Allows the user to compress 2 or 4 pages on to a single A4 sheet

Scan	Scanner Type CIS (Contact Image Sensor)	Scan Resolution from ADF 600 x 600dpi	Colour Depth 30 bit colour Processing (Input) 24 bit colour Processing (Output)
	Colour and Mono Scanning Yes	Scan Resolution from Scanner Glass 1200 x 1200dpi	Grey Scale 10 bit colour Processing (Input) 8 bit colour Processing (Output)
	Scan Speed ³ 22.5ipm Mono and 7.5ipm Colour	Interpolated Scan Resolution Brother Scanner Utility enhances up to 19,200 x 19,200 dpi	

Scanner Functions

Supported File Formats Including PDF (PDF/A, Secure PDF, Signed PDF, Searchable), JPEG, TIFF	Network Scanning ¹⁶ Scan to E-mail Server, Sharepoint (iPrint&Scan for Windows only), FTP, FTPS	Scan To Microsoft Office Scan to Word (.docx), PowerPoint (.pptx), Excel (.xlsx) for Microsoft Office
Standard Functions ¹⁷ Scan to E-mail, OCR , Image, File	Scan Features Auto Deskew from ADF only (iPrint&Scan for Desktop)	Scan Profile ¹⁵ Create up to 25 profiles for an easy way to store multiple scan settings (scan to FTP/ Sharepoint)

Scanner Drivers

Windows TWAIN and WIA Windows 11 (32 and 64 bit editions)	macOS Scanning via macOS requires the use of AirPrint. Mac drivers are not provided.	Linux SANE (32 and 64 bit editions)
Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.		
		ChromeOS Supports native ChromeOS scanning

Fax

Fax Modem 33,600bps (Super G3)	Out of Paper Reception Up to 400 pages (ITU-T Test Chart, Standard Resolution, JBIG)	Memory Transmission Up to 400 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Grey Scale 256 shades (8 bit) of grey are available for faxing	Broadcasting Send the same fax message up to 260 locations	

Fax Functions

Internet Fax (I-Fax) Fax documents over the internet as an email attachment	Fax Forwarding Send a fax received in memory to another pre-programmed fax number	Error Correction Mode (ECM) Detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Fax to Server Scan a document and send it over the network to a separate fax server	Remote Retrieval Allows users to remotely access their machine and retrieve stored fax messages	
Automatic Redial Automatic redialling if the recipient fax is busy	Fax Stamp Add the date and time to all received faxes	Auto Reduction When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
Telephone Index An electronic, alphabetical listing of stored speed dials and group numbers	Cover Page Create custom cover pages for outgoing faxes	
Chain Dialling Allows the user to store parts for long dialing sequences in different speed dial locations	Station ID An ID and fax number will be printed as the header of every fax sent	
	PC-Fax Send and Receive ^{15,18} Send and Receive faxes directly from your PC. Supports mono only	

Address Book

Speed Dials ¹⁷ 200 locations for E-mail addresses and fax numbers	Group Dial ¹⁷ A combination of up to 20 groups can be stored for broadcasting
--	--

Fleet Management Tools

BRAAdmin Pro ^{16,17} LAN/WAN management software	Embedded Web Server Web based print management software embedded onto the device	Status Monitor ¹⁶ Monitor the status of your machine from your computer
	Driver Deployment Wizard ^{16,17} Easily create print drivers for hassle free deployment over your network	

Software

Brother iPrint&Scan Desktop ^{15,17} Print from, scan to, preview copies and check the machine status from Windows or macOS PC	PaperPort SE 14 ^{16,17} Document management and sharing program from KOFAX	Easy Setup Simple access to drivers and software for the installation of your Brother machine from support.brother.com
	Utilities Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service	Windows/Mac

Connectivity

Wired Network
**Fast Ethernet
(10Base-T/100Base-TX)**

Wireless Network
**2.4GHz: IEEE 802.11 b/g/n
(Infrastructure Mode)
IEEE 802.11 g/n (Wi-Fi Direct)**

Wi-Fi Direct^{*}
**Print wirelessly without having
to go through a wireless access
point (both automatic and
manual methods supported)**

Mobile
**Print or scan from your mobile
device with Brother Mobile
Connect, Airprint, Mopria**

Wireless Setup Support
Wi-Fi Protected Setup (WPS)
Wireless Applications
Vertical Pairing

Local Interface
Hi-Speed USB 2.0

Security Features

Wired Network Security
**APOP*, SMTP-AUTH, SSL/TLS
(SMTP, POP3, IMAP4,FTP)*,
SNMP v3, 802.1x (EAP-MD5,
EAP-FAST, PEAP, EAP-TLS,
EAP-TTLS), OAuth(SMTP, POP3,
IMAP4) *When Internet FAX is
downloaded.**

Wireless Network Security
**WEP 64/128 bit, WPA-PSK
(TKIP/AES), WPA2-PSK (TKIP/
AES), WPA3-SAE (AES), WIFI
Direct supports WPA2-PSK
(AES) only.**

IPv4
**ARP, RARP, BOOTP, DHCP,
APIPA(Auto IP), WINS/NetBIOS
name resolution, DNS Resolver,
mDNS, LLMNR responder,
LPR/LPD, Custom Raw Port/
Port9100, POP3, SMTP Client,
IPP/IPPS, FTP Client and Server,
SNMPv1/v2c/v3, HTTP/HTTPS
server, TFTP client and server,
ICMP, Web Services (Print/
Scan), SNMP Client, IMAP4**

IPv6
**NDP, RA, DNS resolver, mDNS,
LLMNR responder, LPR/LPD,
Custom Raw Port/Port9100,
IPP/IPPS,POP3 SMTP Client,
FTP Client and Server, SNMPv1/
v2c/v3, HTTP/HTTPS server,
TFTP client and server, ICMPv6,
Web Services (Print/Scan), SMTP
Client, IMAP4**

IP Filter
**Restrict which network users
can or cannot access the device
over the network (IPv4 only)**

E-mail Notifications
**Automatically have the device
send e-mail alerts when it
requires attention, such as
when the toner is low or needs
replacing**

E-mail Reports
**Receive usage reports on a
regular basis via e-mail**
Setting Lock
**Secures access to the device
control panel by locking it**
Port-based Network
Access Control
**(IEEE 802.1x)
Brother devices are in full
compliance with this standard,
to allow connection to an 802.1x
EAP (Extensible Authentication
Protocol) protected network**

Supplies and Consumables

Inbox Toner⁷
1 x 1,200 pages

Standard Yield Toner⁷
TN2500 - 1,200 pages

High Yield Toner⁷
TN2500XL - 3,000 pages

Drum Unit
**DR2500 Approx 15,000 pages
at 1 page per job**

Dimensions and Weights

With Carton (WxDxH)
580 x 517 x 434mm - 14.10kg

Without Carton (WxDxH)
410 x 399 x 319mm - 10.50kg

Duty Cycle	Recommended Monthly Up to 2,500 pages		
Operating Environment	Power Requirement 220-240V AC 50/60Hz	Operating Environment Humidity 20 - 80 % 10°C - 32.5°C 50°F - 90.5°F	Storage Environment Humidity 35 - 85 % 0°C - 40°C 32°F - 104°F

Environment	Approx Power Consumption ^{13,23} Copying: 480W Copying in quiet mode: 280W Printing: 470W Printing in quiet mode: 270W Ready: 43W Sleep: 4.1W Deep Sleep: 0.6W Power Off: 0.08W TEC Value 0.39 kWh/week	Sound Power ¹² Printing: 6.63B(A) Ready: Inaudible Quiet Mode: 6.12B(A) Deep Sleep: Inaudible Sound Pressure ¹² PC Printing (Mono): Approx. 49.0dB(A) Ready: 30.0db(A) Quiet Mode: 44.0db(A) Toner Save This reduces the toner consumption to get more pages from your consumables
-------------	--	---

Warranty	Brother 3-Year Warranty When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 3-year* warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition, we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 3-year* warranty.
----------	--



*Effective 1 September 2025. Valid only for products purchased in South Africa.

- 3

Scan Speeds based on ISO/IEC 17991
- 7

Approx. declared yield value in accordance with ISO/IEC 19752
- 11

Capacity calculated with 80gsm paper
- 12

Sound pressure and sound power level in accordance with ISO 7779
- 13

Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15

Windows and macOS only
- 16

Windows only
- 17

Optional download
- 18

Requires an Internet connection
- 23

Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration



Brother International South Africa
96 Sovereign Drive, Route 21 Corporate Park, Irene
Tel 0861 brother Email info@brother.co.za
www.brother.co.za https://support.brother.com/

All specifications correct at time of publication and are subject to change without notice. Brother and its logo are trademarks of Brother Industries LTD., Japan. All registered trademarks referenced herein are the property of their respective companies.